

ضبط إعدادات الموجه اللاسلكي

في هذه الخطوة سنقوم بشرح طريقة ضبط إعدادات الموجه اللاسلكي من نوع **Wireless-G ADSL Home Gateway (Linksys WAG200G)** الموضح في الشكل (٤-١). أما من كان يملك موجه من نوع آخر فبإمكانه الرجوع إلى موقع الشركة المنتجة أو شركة الاتصالات التي تقدم خدمة DSL للحصول على إعدادات الموجه اللاسلكي ، مع العلم أن كثير مما سنوضحه ينطبق تماماً على بقية الموجهات اللاسلكية ماعدا اختلاف الواجهات. ولا ننسى أنه يجب أن يكون لدينا بيانات اشتراك DSL واشتراك انترنت (اسم مستخدم وكلمة مرور) من شركة الاتصالات.

- يفضل قبل أن نبدأ أن نوصل الموجه بمنفذ الإيثرنت الخاص بكرت الشبكة السلكي خلف الجهاز حتى نتمكن من دخول صفحة إعدادات المودم.
- في البداية ندخل على صفحة الإعدادات عن طريق متصفح الإنترنت وندخل هذا الرقم في عنوان المتصفح 192.168.1.1.
- عند إدخال الرقم السابق في المتصفح سيطلب منا إدخال اسم المستخدم والرقم السري الافتراضي وهو Admin .
- بعد الدخول إلى صفحة الإعدادات الخاصة بالمودم تظهر معنا الصفحة الرئيسية اتبع الخطوات المشروحة على الصورة.

The screenshot shows the 'Setup' page of the Linksys WAG200G Gateway. The 'Internet Setup' section is expanded, showing 'PVC Connection' and 'Internet Connection Type' set to 'VC Settings'. The 'PPPoE Settings' section is also expanded, showing fields for Service Name, User Name, Password, and options for 'Connect on Demand' and 'Keep Alive'. A white arrow points to the 'User Name' field with the text 'اسم المستخدم وكلمة المرور' (Username and Password).

شكل (٤-٦)